



AMPERAGE SHOWN FOR 3 PHASE AT 80% POWER FACTOR

KVa	kW	208V	220V	240V	480V	600V	4160V
31.3	25	87	82.5	75.5	37.8	30	4.4
37.5	30	104	99	90.3	45.2	36	5.2
50	40	139	132	120	60	48	7
62.5	50	173	165	152	76	61	8.7
75	60	208	198	181	91	71	10.5
93.8	75	261	247	226	113	90	13
100	80	278	264	240	120	96	13.9
125	100	347	330	301	150	120	17.5
156	125	433	413	375	188	150	22
187	150	520	495	450	225	180	26
219	175	608	577	527	264	211	31
250	200	694	660	601	301	241	35
312	250	866	825	751	376	300	43
375	300	1040	990	903	451	361	52
438	350	1220	1155	1053	527	422	61
500	400	1390	1320	1203	602	481	69
665	500	1735	1650	1504	752	602	87
750	600	2080	1980	1803	902	721	104
875	700	2430	2310	2104	1052	842	121
1000	800	2780	2640	2405	1203	962	139
1125	900	3120	2970	2709	1354	1082	156
1250	1000	3470	3300	3309	1504	1202	174
1563	1250	4350	4130	3765	1885	1503	218
1875	1500	5205	4950	4520	2260	1805	261
2188	1750			5280	2640	2106	304
2500	2000			6020	3015	2405	348
2812	2250			6780	3400	2710	392
3130	2500			7520	3765	3005	435
3438	2750			8280	4140	3312	478
3750	3000			9032	4516	3613	521